

MPE/iX HA Product Support Matrix

Version 08/10/2005

| | |
|----------------------------|--|
| Supported | |
| Not Supported | |
| CSY Approval Needed | |

| High Availability Product | MPE/iX Release | | | | |
|---|-------------------------|-------------------------|-------------------------|-------------|-----------|
| | 6.0+PP2 SCSI | 6.5+PP3 SCSI | 7.0+PP2 SCSI | 7.5 | |
| | | | | SCSI | FC |
| 12H (AutoRAID) and ARM Server Support | | | | | |
| HAFO | U | | | | |
| XP256 – SCSI ONLY | N | | | | |
| BC & CA , RAID Manager XP, HAFO* | S | | | | |
| XP512 & XP48 – (+FC Hubs and Switches) | U | Requires A5814A#003 | Requires A5814A#003 | A5814A#003 | |
| BC & CA, RAID Manager XP, HAFO* | S | " | " | " | |
| XP1024 & XP128- (+FC Hubs and Switches) | U | Requires A5814A#003 | Requires A5814A#003 | A5814A#003 | |
| BC & CA, RAID Manager XP , HAFO* | S | " | " | " | |
| XP12000 & XP10000 (+FC Switches) | U | Requires A5814A#003 | Requires A5814A#003 | A5814A#003 | |
| BC & CA, RAID Manager XP , HAFO* | S | " | " | " | |
| VA7400 –FC UNSUPPORTED | P | | | | |
| VA7100 –FC (+ FC Hubs and Switches) | O | | Requires A5814A#003 | A5814A#003 | |
| Business Copy | R | | | | |
| HAFO | T | | | | |
| VA7110 , VA7410 (+FC Hubs and Switches) | E | | Requires A5814A#003 | A5814A#003 | |
| Business Copy | D | | | | |
| HAFO (Patch MXH5 & MXG9 or greater required for MPE/iX 7.0 & 7.5) | | " | " | " | |
| Cluster/iX | | | | | |
| Heartbeat | | | | | |

* HAFO requires patches MXH5 & MXG9 or greater for MPE/iX 7.0 & 7.5

Supported Switches: Brocade 2400/2800 Silkworm Switches, FC64 and HP 1/2Gb/s FC Switch 8B and 16B. This is not a complete list of switches, please go to HP's website for a complete list and more information. <http://www.hp.com/products/storage/products/san/fibreswitches/index.html>

A5814A-SCSI Router only supports:

- 1 A SCSI device distancing solution for SCSI HVD devices such as the HASS (Jamaica) Enclosure, 12H Autoraid and XP256-SCSI.
No support for Mirrored Disk/iX, FC switches nor Dump disks using the distancing solution.
- 2 Direct connect to XP512 array
No support for any FC switches or hubs.

A5814A-003 SCSI Fabric Router only supports:

- 1 XP12000, XP1024/XP128, XP512/XP48, VA7100, VA7110 and VA7410 with HP's supported portfolio of hubs and FC switches.
- 2 No support of tapes.

Mirrored Disk/iX is only supported on JBOD enclosures like the DS2100 and DS2300. No support of distancing routers and disk arrays.

Cluster/iX Hardware Support List: Model-20, 12H AutoRAID, VA7xxx, XP256, XP512/XP48, XP1024/XP128 & XP12000. Limited support on EMC Symmetrix.